



Transmit



Receive



Decode



Control

## Multi Channel Transmitter RT22 BaseWave

Of the Multi Channel Transmitter RT22 three different models are available:

### 52-channel-model:

Up to 52 devices can be controlled and 4 different levels each containing 13 individually coded radio channels are provided.

### 999-channel-model (impulse mode):

Up to 999 devices can be selected by a numerical code. The transmission is activated by pressing ENTER. With the buttons A to D it is possible to switch one device each directly.

### 999-channel-model (awning mode):

Up to 999 devices can be selected by a numerical code. It can then be controlled by pressing UP/STOP/DOWN. With the buttons A to D it is possible to switch one device each directly.



RT22-XX39M-01

### Technical Details

Coding	factory coding with over 70 million options, code duplication by the user is possible
Channels	52 or 999
Range	up to 150 m under favourable open field conditions
Power Supply	2x 3V battery, CR2032
Operation Indicator	4 LED's
Degree of Protection	IP54
Operating Temperature	-20 °C to +60 °C
Dimensions	60 x 150 x 22 mm
Weight	100 g (including battery)

### Accessories






RT22-ACC-01



ACC-CAB-11

### Models



### Scope of Delivery

Multi Channel Transmitter  
incl. battery  
Mounting Plate  
Programming Cable  
Operating Manual

### Accessories (optional)

Mounting Plate  
Programming Cable  
Battery

### Product Key

52 Channels (pulse)	999 Channels (pulse)	999 Channels (direction)
on request	RT22-3139M-01	on request
RT22-4125M-01	RT22-4139M-01	RT22-4139M-02
RT22-5025M-01	RT22-5039M-01	RT22-5039M-02
on request	on request	on request

### Description

### Frequency

RT22-ACC-01	Mounting Plate	315.00 MHz
ACC-CAB-11	Programming Cable	433.92 MHz
ACC-BAT-05	Battery CR2032	868.30 MHz
		916.50 MHz