



Transmit



Receive



Decode



Control

Necklace Transmitter RT27

BaseWave

The Necklace Transmitter RT27 allows an easy operation of commands, e.g. comfortable operation of lights or other electric devices.

It also includes a battery-check-function which is represented by a flashing LED that shows low battery capacity.

The RT27 can be used in an area of splashing water.



RT27-XX01M-01

Technical Details

Coding	factory coding with over 70 million options
Channel	1 (1 button)
Range	up to 150 m under favourable open field conditions
Power Supply	1x 3V battery, CR2032
Operation Indicator	LED
Control	transmission lasts for as long as button is pressed (but max. 36 s)
Degree of Protection	IP65
Operating Temperature	-20 °C to +60 °C
Dimensions	Ø 41 x 13 mm
Weight	16 g (including battery)

Scope of Delivery

- Necklace Transmitter incl. battery
- Necklace (standard)
- Operating Manual

Accessories (optional)

- Battery Exchange Set
- Necklace (standard)
- Necklace (predetermined breaking point)
- Battery

Accessories



RT26-ACC-01



RT27-ACC-02



RT27-ACC-05

Models

Product Key	Description	Frequency
on request	Necklace Transmitter	315.00 MHz
RT27-4101M-01	Necklace Transmitter	433.92 MHz
RT27-5001M-01	Necklace Transmitter	868.30 MHz
on request	Necklace Transmitter	916.50 MHz
RT26-ACC-01	Battery Exchange Set	
RT27-ACC-02	Necklace (standard)	
RT27-ACC-05	Necklace (predetermined breaking point)	
ACC-BAT-05	Battery	