



Transmit



Receive



Decode



Control

Radio Wall Switch RTS14

Easywave

The Radio Wall Switch RTS14 can be installed wall-mounted in dry rooms.

It can be fitted to usual switches, pasted on walls or screwed onto the wall.

Depending on the model and the Easywave-Receiver used, the RTS14 can be used to switch electrical consumers with one-button-operation, in two-button-operation or for the control of shutters / awnings.



RTS14-5003E-01

Technical Details

Coding	factory coding with Easywave Telegram
Channels	2, 3 or 6
Range	up to 150 m under favourable open field conditions
Power Supply	1x 3V battery, CR2032
Control	transmission lasts for as long as button is pressed (but max. 36 s)
Operation Modes	depending on the receiver; see model
Degree of Protection	IP30
Operating Temperatur	-20 °C to +50 °C
Dimensions	80 x 80 x 10 mm
Weight	42 g (including battery)
Color	white (Signalweiß RAL 9003)

Scope of Delivery

- Radio Wall Switch incl. battery
- Mounting Accessories
- Operating Manual

Accessories (optional)

- Battery ACC-BAT-05

Models

Product Key	RTS14-5002E-01	RTS14-5003E-01	RTS14-5006E-01
Frequency	868.30 MHz	868.30 MHz	868.30 MHz
Description	Radio Wall Switch	Radio Wall Switch	Radio Wall Switch
Operation Modes	2x UP/STOP/DOWN	3x ON/OFF	6x Pulse

